

APPLICATION

FOR

UNITED STATES LETTERS PATENT

TITLE: MULTIMODE AND MULTIBAND MIMO TRANSCEIVER
OF W-CDMA, WLAN AND UWB COMMUNICATIONS

INVENTOR: GEORGE J. MIAO

Express Mail No.: ER 237057437 US

Date: 12/27/2003

MULTIMODE AND MULTIBAND MIMO TRANSCEIVER OF
W-CDMA, WLAN AND UWB COMMUNICATIONS

Background

This invention is generally relative to a multimode and multiband Multiple-Input-Multiple-Output (MIMO) transceiver of Wideband Code Division Multiple Access (W-CDMA), Wireless Local Area Network (WLAN), and Ultra
5 Wideband (UWB) Communications for a wireless and fixed wireless communication.

The MIMO is a multiple-input-multiple-output as a wireless link and is also known as a space-time signal processing that a natural dimensional of transmitting data
10 is complemented with a spatial dimension inherent in the use of multiple spatially distributed antennas. The MIMO is able to turn multipath propagation into benefit for service provider and wireless users. This is because signals on the transmit antennas at one-end and the receiver antennas at
15 the other-end are integrated such that a quality of bit error rate (BER) or a data rate of the communication for each wireless user or a transmitting distance is improved, thereby increasing a communication network's quality of service.

20 The W-CDMA is a wideband, spread spectrum radio interface that uses CDMA technology to meet the needs for wireless communication systems, which allow subscribers to access World Wide Web or to perform file transfers over

packet data connections capable of providing 144 kbps and 384 kbps for mobility, and 2 Mbps in an indoor environment. The W-CDMA (also known as CDMA2000) supports for a wide range of radio frequency (RF) channel bandwidths from 1.25 MHz to 15 MHz with operating of 1.90 GHz band, where the channel sizes of 1, 3, 6, 9, and 12×1.25 MHz. The wide channels of the W-CDMA offer any combination of higher data rates, increase total capacity and/or increase range. The W-CDMA also employs a single carrier and a multicarrier system, which can be deployed as an overlay over one or more existing the second generation of TIA/EIA-95B 1.25 MHz channels. In the multicarrier system, modulation symbols are de-multiplexed onto N separate 1.25 MHz carrier, where each carrier is spread with a 1.2288 Mcps chip rate.

The WLAN is an IEEE standard for wireless LAN medium access control (MAC) and physical layer (PHY) specification and is also referred to as the high-speed physical layer (802.11a) in the 5 GHz band. The WLAN standard specifies a PHY entity for an orthogonal frequency division multiplexing (OFDM) system. The RF LAN communication system is initially aimed for the lower band of the 5.15 - 5.35 GHz and the upper band of the 5.725 - 5.825 GHz unlicensed national information structure (U-NII) bands, as regulated in the United States by the code of Federal Regulations under Title 47 and Section 15.407. The WLAN communication system provides the data payload rate of 6, 9, 12, 18, 24,

36, 48 and 54 Mbit/s. Also, the WLAN communication system supports the transmitting and receiving at data rate of 6, 12, and 24 Mbit/s with mandatory. The WLAN communication system uses 52 subcarriers with modulation of using binary or quadrature phase shift keying (BPSK/QPSK), 16-quadrature amplitude modulation (QAM), or 64-QAM. The forward error correction coding (FEC) of convolution encoding is used with a coding rate of 1/2, 2/3, or 3/4.

U.S. Federal Communications Commission (FCC) released a revision of Part 15 of Commission's rules with regard to UWB communications to permit the marketing and operation of certain types of new products on April 22, 2002. UWB communication systems can operate using spectrum occupied by existing radio service without causing interference, thereby permitting scarce spectrum resources to be used more efficiently. The UWB communication systems can offer significant benefits for Government, public safety, businesses and consumers under an unlicensed basis of operation spectrum.

FCC is adapting unwanted emission limits for the UWB communication devices that are significantly more stringent than those imposed on other Part 15 devices. For the indoor UWB operation, FCC provides a wide variety of UWB communication devices, such as high-speed home and business networking devices under the Part 15 of the Commission's rules subject to certain frequency and power limitations.

However, the UWB communication devices must operate in the frequency band ranges from 3.1 GHz to 10.6 GHz, and have an emission of -10 dBm for the UWB operation. In addition, the UWB communication devices should also satisfy the Part 15.209 limit for the frequency band below 960 MHz. Table 1 lists the FCC restriction of the emission masks (dBm) along with the frequencies (GHz) for the UWB communication devices in the indoor environment.

Table 1

| Frequency (MHz) | EIRP (dBm) |
|-----------------|------------|
| 0-960 | -41.3 |
| 960-1610 | -75.3 |
| 1610-1990 | -53.3 |
| 1990-3100 | -51.3 |
| 3100-10600 | -41.3 |
| Above 10600 | -51.3 |

The UWB communication devices are defined as any devices where the fractional bandwidth is greater than 0.25 based on the formula as follows:

$$FB = 2 \left(\frac{f_H - f_L}{f_H + f_L} \right), \quad (1)$$

where f_H is the upper frequency of -10 dBm emission points, and f_L is the lower frequency of -10 dBm emission points. A center transmission frequency F_c of the UWB communication devices is defined as the average of the upper and lower -10 dBm points as follows:

$$F_c = \frac{f_H - f_L}{2}. \quad (2)$$

Furthermore, a minimum frequency bandwidth of 500 MHz must be used for the indoor UWB communication devices regardless of center frequencies.

5 The UWB communication products can be used for fixed wireless communications within a short-distance range, particularly for a very high-speed data transmission suitable for broadband access to networks in the indoor environment.

10 The multimode and multiband MIMO transceiver of W-CDMA, WLAN and UWB communication system is disclosed herein according to some embodiments of the present invention. The invented transceiver system is a MIMO-based multimode and multiband portable station with integrating
15 of W-CDMA, WLAN, and UWB communication. The portable station employs four antennas at the transmitter and receiver as a MIMO link. During the wireless communications, the W-CDMA in the portable station has a multicarrier for 12 channels with a total of 15-MHz
20 frequency bandwidth at the center of 1.9 GHz frequency band and is able to transmit the data rate more than 2 Mbps. The W-CDMA can be used as a user phone with enable of communicating speech, data, image, and clip video. On the other hand, during the fixed wireless communications, the
25 WLAN in the portable station can transmit and receive the

data rate up to 54 Mbps based on OFDM technology at the
unlicensed national information structure (U-NII) bands of
the 5.15 - 5.35 GHz and the upper band of the 5.725 - 5.825
GHz. The UWB communication in the portable station uses an
5 OFDM-based multicarrier for four-multiband with each
multiband of frequency bandwidth about 512 MHz in the
frequency range from 3.1 GHz to 5.15 GHz and is able to
transmit the data rate at 1.5 Gbps. Since the UWB
communication can transmit and receive a very-high data
10 rate but with a very short-distance range while the WLAN is
able to transmit and receive the lower data rate in a much
longer distance range than the UWB communication. Thus, a
combination of the W-CDMA, WLAN, and the UWB communication
in a specific portable device is enable a user to have
15 internet surf, to listen MP3 music, to watch DVD, to play
video game, to view stock graph, to transmit data with
other devices in a real-time operation. Therefore, a trade-
off benefit of W-CDMA, WLAN, and UWB can be utilized each
other, thereby having a co-existence of the multimode and
20 multiband portable station with multiply applications in a
multiply environment.

The present invention of the multimode and multiband
MIMO transceiver of W-CDMA, WLAN, and UWB communications
utilizes both benefits of a wireless phone and a fixed
25 wireless broadband communication. Such a multimode device
not only can transmit the packet data in a form of wireless

phone environment but also can use as a very-high speed wireless broadband Internet device to transmit and receive data, image, video, video game, music, and stock graph in a real-time. Therefore, there is a continuing need of the multimode and multiband MIMO transceiver of W-CDMA, WLAN, and UWB communication system for delivering a very-high data rate with a capability of flexibility and scalability in a combination form of wireless and fixed wireless environment.

Summary

In accordance with one aspect, a multimode and multiband MIMO transceiver of W-CDMA, WLAN and UWB communication comprises a MIMO-based multimode and multiband RF unit of W-CDMA, WLAN and UWB, a W-CDMA rake and baseband processor, a dual-mode WLAN and UWB OFDM processor, a tri-mode interleaver, a tri-mode coding processor, a sharing memory bank, a tri-mode control processor of W-CDMA, WLAN and UWB, and a multiple antenna unit including four identical antennas.

Other aspects are set forth in the accompanying detailed description and claims.

Brief Description of the Drawings

FIG. 1 is a block diagram of showing a multimode and multiband MIMO transceiver of W-CDMA, WLAN and UWB communication according to some embodiments.

FIG. 2 is a detailed block diagram of showing a multimode and multiband RF receiver section of W-CDMA, WLAN and UWB communication according to some embodiments.

FIG. 3 is a detailed block diagram of showing a tri-mode analog-to-digital (A/D) converter unit according to some embodiments.

FIG. 4 is a detailed block of showing a W-CDMA rake-based baseband processor according to some embodiments.

FIG. 5 is a detailed block diagram of showing a dual-mode WLAN and UWB OFDM processor according to some embodiments.

FIG. 6 is a detailed block diagram of showing a dual-mode WLAN and UWB Fast Fourier transform (FFT) and frequency-domain equalizer (FEQ) unit according to some embodiments.

FIG. 7 is a detailed block diagram of showing a multiband UWB digital receiver filter, despreading, and time-domain equalizer (TEQ) unit according to some embodiments.

FIG. 8 is a detailed block diagram of showing an UWB FFT and FEQ unit according to some embodiments.

FIG. 9 is a frequency spectrum output of the multiband UWB communication system according to one embodiment.

FIG. 10 is a block diagram of showing an implementation flowchart for multimode and multiband MIMO

transceiver of W-CDMA, WLAN, and UWB communication according to some embodiments.

Detailed Description

Some embodiments described herein are directed to the multimode and multiband MIMO transceiver of W-CDMA, WLAN, and UWB communication for the wireless and fixed wireless communication. Such the multimode and multiband MIMO transceiver system may be implemented in hardware, such as in an Application Specific Integrated Circuits (ASIC), digital signal processor, field programmable gate array (FPGA), software, and/or a combination of hardware and software.

Transceiver System and Architecture

Portable station architecture of the multimode and multiband MIMO transceiver of W-CDMA, WLAN, and UWB communication system 100 for the wireless and fixed wireless communication is shown in FIG. 1 in accordance with one embodiment of the present invention. The portable station architecture of the multimode and multiband MIMO transceiver includes a multimode and multiband RF unit of W-CDMA, WLAN, and UWB communication 120, a W-CDMA rake and baseband processor 130, a dual-mode WLAN and UWB OFDM processor 140, an interleaver/deinterleaver unit 150, a coding/decoding processor 160, a sharing memory bank 170, and a tri-mode control processor of W-CDMA, WLAN and UWB

180. The multimode and multiband RF unit of W-CDMA, WLAN, and UWB communication 120, which is coupled to four identical and independent antennas of 110a to 110d, is used to convert baseband signals of W-CDMA, WLAN or UWB into RF signals for a transmitter and/or convert RF signals of W-CDMA, WLAN and UWB into baseband signals for a receiver. During W-CDMA mode, the multimode and multiband RF unit of W-CDMA, WLAN, and UWB communication 120 connects to a W-CDMA rake and baseband processor 130, which deals with a rake processing, a scramble/descramble, and a spreading/dispreading. The W-CDMA rake and baseband processor 130 is coupled to a tri-mode interleaver unit 150 that performs an interleaver and deinterleaver for W-CDMA signals. The tri-mode interleaver unit 150 is connected with a tri-mode coding processor 160 that is used to perform encoding and/or decoding for a user data stream. During a WLAN or UWB mode, the multimode and multiband RF unit of W-CDMA, WLAN, and UWB communication 120 connects to a dual-mode WLAN and UWB OFDM processor 140, which performs a time-domain equalizer (TEQ), an OFDM, a frequency-domain equalizer (FEQ), and/or a multiband spreading/despreading. The dual-mode WLAN and UWB OFDM processor 140 is coupled to the tri-mode interleaver unit 150, which performs an interleaver and deinterleaver for WLAN or UWB signals. The tri-mode interleaver unit 150 is connected with a tri-mode coding processor 160 that is used to perform encoding

and/or decoding for a user data stream during WLAN or UWB communications. The control processor 180 of W-CDMA, WLAN and UWB is used to control frame data flows with exchanging between all of the processors of 130, 140, and 160, and
5 units of 120, 150 and the sharing memory bank 170.

The portable station system and architecture 100 of the multimode and multiband MIMO transceiver of W-CDMA, WLAN, and UWB communication is used for the wireless and fixed wireless communication. For the wireless
10 communication, the portable station system and architecture 100 can transmit and receive the W-CDMA data rate stream from 144 kbps to greater than 2 Mbps, and supports for a range of RF channel bandwidths including 1.25 MHz, 3.75 MHz, 7.5 MHz, 11.25 MHz, and 15 MHz at the center frequency
15 of 1.9 GHz. For the fixed wireless communication, the portable station system and architecture 100 can be used either as a WLAN transceiver or as an UWB transceiver. During WLAN mode, the portable station system and architecture 100 can transmit and receive the WLAN data
20 rate up to 54 Mbps at the unlicensed national information structure (U-NII) bands of the 5.15 - 5.35 GHz and the upper band of the 5.725 - 5.825 GHz. During UWB mode, the portable station system and architecture 100 is used to transmit and receive the UWB data rate up to 1.5 Gbps based
25 on OFDM-based multicarrier and multiband of frequency bandwidth in the frequency range from 3.1 GHz to 5.15 GHz,

with an enhancement of transmitting range due to use of the multiple antennas.

Receiver Architecture

5 Referring to FIG. 2 is a detailed block diagram 200 of showing the multimode and multiband RF unit of W-CDMA, WLAN, and UWB communication 120 according to some embodiments. Four analog bandpass filters of 210a to 210d connect to four low noise amplifiers (LNA) of 220a to 220d,
10 followed by four automatic gain controls (AGC) of 230a to 230d. Setting parameters of the analog bandpass filters of 210a to 210d, the LNA of 220a to 220d, and the AGC of 230a to 230d is controllable according to one of modes for W-CDMA, WLAN, or UWB communication. The output signals of the
15 AGC of 230a to 230d are then added together by using a sum over a block 240. During W-CDMA mode, the output W-CDMA signals of the sum over a block 240 is connected with a W-CDMA down converter and demodulation 260 by using a selection switch 252 in a switch unit 250. Thus, the W-CDMA
20 down converter and demodulation 260 produces two I and Q baseband analog signals, g_1 and g_2 , for a tri-mode A/D converter unit 290. The tri-mode A/D converter unit 290 produces two digital baseband signals of au_1 and au_2 . During WLAN mode, the output WLAN signals of the sum over the
25 block 240 are connected with a WLAN down converter and demodulation 270 by using the selection switch 252 in the

switch unit 250. The WLAN converter and demodulation of 270 produces two I and Q baseband analog signals, w_1 and w_2 , for the tri-mode A/D converter unit 290. The tri-mode A/D converter unit 290 produces two digital baseband signals of
5 au_1 and au_2 . During UWB mode, the output UWB signals of the sum over the block 240 are connected to a multiband UWB down converter and demodulation 280 by using the switch 252 in the switch unit 250. The multiband UWB down converter and demodulation 280 produces eight I and Q baseband analog
10 signals, u_1, u_2, \dots, u_8 for the tri-mode A/D converter unit 290. The tri-mode A/D converter unit 290 produces eight digital baseband signals of au_1, au_2, \dots, au_8 .

Referring to FIG. 3 is a detailed block diagram 300 of showing the tri-mode A/D converter unit 290 according to
15 some embodiments. There are two switch units of 310 and 320 and eight A/D converters of 330a to 330h, with a sampling frequency rate at 540 MHz. During W-CDMA mode, a switch 312 of a switch unit 310 and a switch 322 of a switch unit 320 connect to the input signals of g_1 and g_2 , respectively. The
20 outputs of the switch units of 310 and 320 are passed into two A/D converters of 330a and 330b, with the sampling frequency rate at 540 MHz. This is an over-sampling for the W-CDMA signals. Other A/D converters of 330c to 330h are rest. The output signals au_1 and au_2 of the A/D converters
25 of 330a and 330b are used for the W-CDMA rake and baseband processor. During the WLAN mode, the switch 312 of the

switch unit 310 and the switch 322 of the switch unit 320 connect to the input signals of w_1 and w_2 , respectively. The outputs of the switch units of 310 and 320 are passed into two A/D converters of 330a and 330b, with the sampling
5 frequency rate at 540 MHz. This is an over-sampling for the WLAN signals. Other A/D converters of 330c to 330h are rest. The output signals au_1 and au_2 of the A/D converters of 330a and 330b are used for the dual-mode WLAN/UWB baseband processor. During UWB mode, the switch 312 of the
10 switch unit 310 and the switch 322 of the switch unit 320 connect to the input signals of u_1 and u_2 , respectively. The outputs of the switch units of 310 and 320 along with other six input signals of u_3 to u_8 are in parallel passed into eight A/D converters of 330a and 330h, with the sampling
15 frequency rate at 540 MHz. The output signals of au_1 to au_8 of the A/D converters of 330a to 330h are used for the dual-mode WLAN/UWB baseband processor.

Referring to FIG. 4 is a detailed block diagram 400 of showing the W-CDMA rake and baseband processor 130
20 according to some embodiments. Two input digital signals of au_1 and au_2 are passed through two digital receiver filters of 410a to 410b, followed by two down-sampling of 420a to 420b. A combination of digital receiver filter 410a and the down-sampling 420a, and a combination of the digital
25 receiver filter 410b and the down sampling 420b are to form two digital decimation filters, respectively. The outputs

of the down-sampling of 420a to 420b are multiplexed together by using a MUX 430. The output of the MUX 430 is despread with a sequence from a desreader generator 442. The despread signals of a spreader 440 output are passed
5 through a rake receiver unit 450. Then, the output of the rake receiver unit 450 is descrambled with a sequence of a descrambler coder generator 462 by using a spreader 460. The output of the spreader 460 is used for deinterleaver.

FIG. 5 is a detailed block diagram 500 of showing a
10 dual-mode WLAN and UWB OFDM processor 140 according to some embodiments. During WLAN operation, the input signals of au_1 and au_2 are passed into a WLAN digital decimation channel select filter unit 510 in which produces desired digital downsampled signal sequence. By connecting a switch 532 to
15 a position of a in a switch unit 530, the output of the WLAN digital decimation channel select filter unit 510 is passed through a dual-mode WLAN and UWB, serial-to-parallel (s/P) and guard removing unit 540 to produce 64 parallel signals for a dual-mode WLAN and UWB FFT and FEQ unit 542.
20 The WLAN and UWB FFT and FEQ unit 542 performs 64-point FFT and FEQ operation followed by a P/S unit 546 to convert 64 parallel signals into a serial output signal. On the other hand, during UWB operation, the input signals from au_1 to au_8 are passed into a multiband UWB digital receiver filter
25 desspreading and TEQ unit 520 to produce 4 parallel signals. The first output signal s_1 connects to the dual-mode WLAN

and UWB S/P and guard-removing unit 540 to produce 1024 parallel signals by connecting the switch 532 into a position b in the switch unit 530. Then, the 1024 output signals of the dual-mode WLAN and UWB S/P and guard-removing unit 540 pass through the dual-mode WLAN and UWB FFT and FEQ unit 542 to produce 512 parallel signals for the P/S unit 546, which converts 512 parallel signals into a serial signal for a P/S unit 560. Other output signals of s_2 to s_4 from the multiband UWB digital receiver filter, despread and TEQ unit 520 in parallel pass three S/P and guard removing units of 550b to 550d. Each of S/P and guard removing units of 550b to 550d produces 1024 parallel signals for FFT and FEQ units of 552b to 552d followed by P/S units of 554b to 554d to produce a serial signal. Then the P/S unit 560 converts the output signals of the P/S unit 546, and the P/S unit 554b-554d to produce one single output signal in which is despread with a sequence from a user key generator 580 by using a spreader 570.

FIG. 6 is a detailed block diagram 600 of showing a dual-mode WLAN and UWB FFT and FEQ unit 542 according to some embodiments. This unit includes a 1024-point FFT 610, a WLAN/UWB mode 660, 500 equalizers 620a₁ to 620a₅₀₀, 500 decision detectors 630a₁ to 630a₅₀₀, 500 subtractors 640a₁ to 640a₅₀₀, and an adaptive algorithm 650. During WLAN mode, the 1024-point FFT 610 only performs 64-point FFT operation under controlling by the WLAN/UWB mode 660. The 64

equalizers 620a₁ to 620a₆₄, 64 decision detectors 630a₁ to 630a₆₄, and 64 subtracts 640a₁ to 640a₆₄ are used along with the adaptive algorithm 650 for update the equalizer taps. Thus, the dual-mode WLAN and UWB FFT and FEQ unit 542

5 produces 64 parallel output signals. During UWB mode, the 1024-point FFT 610 has 1024 inputs and produces 512 outputs in which are used for 500 equalizers 620a₁ to 620a₅₀₀, 500 decision detectors 630a₁ to 630a₅₀₀, and 500 subtracts 640a₁ to 640a₅₀₀. The adaptive algorithm 650 is used to adjust the

10 equalizer taps. The adaptive algorithm is one type of algorithms including a least mean square (LMS), a recursive least squares (RLS) or a constant modulus algorithm (CMA). As a result, in this case, the dual-mode WLAN and UWB FFT and FEQ unit 542 produces 500 parallel output signals.

15 FIG. 7 is a detailed block diagram 700 of showing the multiband UWB digital receiver filter, despreading and TEQ unit 520 according to some embodiments. The input UWB signals au₁ to au₂ in parallel pass through eight digital receiver filters 710a₁ and 710a₂, to 720d₁ and 720d₂. Each of

20 the digital receiver filters 710a₁ and 710a₂ to 720d₁ and 720d₂ is followed by one of spreading unit 720a₁ and 720a₂ to 720d₁ and 720d₂ to perform a despreading operation. Each of despreading sequences is generated by each of multiband despreading units 730a to 730d, respectively. Then, the

25 output despreaded signals of the spreading units 720a₁ and 720a₂ are multiplexed together by using a MUX 740a, followed

by using a time-domain equalizer (TEQ) 750a. In a similar way, the output despread signals of the spreading units 720d₁ and 720d₂ are multiplexed together by using a MUX 740d, followed by using a TEQ 750d.

5 FIG. 8 is a detailed block diagram 800 of showing a FFT and FEQ unit 552 (for 552b to 552d) according to some embodiments. This unit includes a 1024-point FFT 810, 500 equalizers 820a₁ to 820a₅₀₀, 500 decision detectors 830a₁ to 830a₅₀₀, 500 subtracts 840a₁ to 840a₅₀₀, and an adaptive
10 algorithm 850. The 1024-point FFT 810 has 1024 inputs and produces 512 outputs in which are used for 500 equalizers 820a₁ to 820a₅₀₀, 500 decision detectors 830a₁ to 830a₅₀₀, and 500 subtracts 840a₁ to 840a₅₀₀. The adaptive algorithm 850 is used to adjust the equalizer taps. Thus, the FFT and FEQ
15 unit 552 produces 500 parallel output signals for UWB mode.

UWB Output Spectrums

FIG. 9 is an output UWB frequency spectrum 900 of a multimode and multiband MIMO transceiver of W-CDMA, WLAN
20 and UWB communication transmitter, including four multi-frequency band spectrums of 920, 930, 940 and 950 according to some embodiments. A FCC emission limitation 910 for UWB operation is also shown in FIG. 9. Each transmitter frequency bandwidth of all the multi-frequency band
25 spectrums of 920, 930, 940 and 950 is 512 MHz and is fitted under the FCC emission limitation 910 with different

carrier frequencies. The detail positions of each transmitter multi-frequency band spectrums (dBm) along with the center, lower and upper frequencies (GHz) as well as the channel frequency bandwidth (MHz) are listed in Table 1:

Table 1

| Multichannel Label | Center Frequency (GHz) | Lower Frequency (GHz) | Upper Frequency (GHz) | Frequency Bandwidth (MHz) |
|--------------------|------------------------|-----------------------|-----------------------|---------------------------|
| 920 | 3.357 | 3.101 | 3.613 | 512 |
| 930 | 3.869 | 3.613 | 4.125 | 512 |
| 940 | 4.381 | 4.125 | 4.637 | 512 |
| 950 | 4.893 | 4.637 | 5.149 | 512 |

Implementation Flowchart in the Receiver

FIG. 10 is a block diagram 1000 of showing an implementation flowchart for a multimode and multiband MIMO receiver of W-CDMA, WLAN and UWB communications according to some embodiments. In a receive mode 1020, the output of the receiver mode 1020 passes through a W-CDMA 1030 to determine whether a received signal is W-CDMA, WLAN or UWB. If the received signal is W-CDMA, the multimode and multiband MIMO receiver is then to complete the following steps: 1) set W-CDMA parameters of bandpass filter, LNA and AGC 1050; 2) switch to W-CDMA down converter and demodulation 1052; 3) select two A/D converters 1054 for W-CDMA signals; 4) set W-CDMA parameters for deinterleaver

and decoding 1056. If the received signal is WLAN, then,
the multimode and multiband MIMO receiver is to accomplish
the following steps: 1) set WLAN parameters of bandpass
filter, LNA and AGC 1062; 2) switch to WLAN down converter
5 and demodulation 1064; 3) select two A/D converters for
WLAN signals; and 4) set WLAN parameters for FFT, FEQ,
deinterleaver and decoding 1068. If the received signal is
UWB, then, the multimode and multiband MIMO receiver is to
finish the following steps: 1) set UWB parameters of
10 bandpass filter, LNA and AGC 1072; 2) switch to UWB down
converter and demodulation 1074; 3) select eight A/D
converters 1076 for UWB signals; 4) set UWB parameters for
FFT, FEQ, deinterleaver and decoding 1078.

While the present inventions have been described with
15 respect to a limited number of embodiments, those skilled
in the art will appreciate numerous modifications and
variations therefrom. It is intended that the appended
claims cover all such modifications and variations as fall
within the true spirit and scope of these present
20 inventions.

What is claimed is:

1